

What We Claim Is:

1           1.     A method for estimating channel characteristics in a multicarrier transmission  
2     system comprising the steps of:

3                     receiving a multicarrier signal;  
4                     applying Fast Fourier transformations to carriers of said multicarrier signal;  
5                     estimating channel characteristics of a multicarrier channel over which said  
6     multicarrier signal was transmitted using iterative processing; and  
7                     decoding said transformed multicarrier signal.

1           2.     The method according to claim 1, wherein said iterative processing further  
2     comprises the steps of:

3                     determining if a block in a frame in the received signal is a training block;  
4                     tentatively decoding said block of said received signal;  
5                     calculating a tentative reference signal based on a previous training block;  
6                     generating a tentative estimation of channel characteristics using said tentative  
7     reference signal;  
8                     decoding said block of said received signal;  
9                     calculating a reference signal based on said received block;  
10                    generating an estimation of channel characteristics using said reference signal;  
11                    incrementing the block number;  
12                    determining if the end of said frame has been reached;

accepting a next block of received signal if said end of said frame has not been reached; and  
iteratively performing the steps above.

3. The method according to claim 2, wherein said decoding steps are performed using  $\hat{\mathbf{c}}_n = \arg \min_{\mathbf{c}_n} \sum_m \|\mathbf{x}_{m,n} - \hat{\mathbf{H}}_{m,n} \mathbf{c}_n\|^2$ .

4. The method according to claim 2, wherein said calculating steps are performed using  $\tilde{\mathbf{H}}_{m,n} = \arg \min_{\mathbf{H}_{m,n}} \sum_m \|\mathbf{x}_{m,n} - \mathbf{H}_{m,n} \hat{\mathbf{c}}_n\|^2$ .

5. The method according to claim 2, wherein said first generating step is performed using  $\sum_{l=1}^{M_L} \mathbf{B}_l \mathbf{d}(\tilde{\mathbf{H}}_{m,n+1-l}) - \mathbf{d}(\hat{\mathbf{H}}_{m,n}) = 0$

6. The method according to claim 2, wherein said second generating step is performed using  $\sum_{l=1}^{M_L} \mathbf{B}_l \mathbf{d}(\tilde{\mathbf{H}}_{m,n+1-l}) - \mathbf{d}(\hat{\mathbf{H}}_{m,n+1}) = 0$ .

7. The method according to claim 1, wherein said decoding step further comprises the steps of:  
demodulating said multicarrier received signal;  
combining said demodulated multicarrier signal using a maximum ratio combiner; and  
Viterbi decoding said combined signal.

1           8.     The method according to claim 7, further comprising the step of  
2     deinterleaving said combined signal if said combined signal was interleaved for transmission.

1           9.     The method according to claim 2, wherein said decoding step further  
2     comprises the steps of:

3                 demodulating said multicarrier received signal;

4                 combining said demodulated multicarrier signal using a maximum ratio  
5     combiner; and

6                 Viterbi decoding said combined signal.

1           10.    The method according to claim 9, further comprising the step of deinterleaving  
2     said combined signal if said combined signal was interleaved for transmission.

1           11.    The method according to claim 7, wherein said demodulating step is  
2     performed concurrently for all signals of said multicarrier signal.

1           12.    The method according to claim 9, wherein said demodulating step is  
2     performed concurrently for all signals of said multicarrier signal.

1           13.    The method according to claim 2, wherein said first generating step is  
2     performed using  $\sum_{l=1}^{M_1} \mathbf{b}_l^T \tilde{\mathbf{H}}_{m,n+1-l} - \hat{\mathbf{H}}_{m,n} = 0$ .

1           14.    The method according to claim 2, wherein said second generating step is  
2     performed using  $\sum_{l=1}^{M_1} \mathbf{b}_l^T \tilde{\mathbf{H}}_{m,n+1-l} - \hat{\mathbf{H}}_{m,n+1} = 0$ .

1           15.    The method according to claim 1, wherein Fast Fourier transformations are  
2   applied to each carrier of said multicarrier signal.

1           16.    A method for estimating channel characteristics in a multicarrier transmission  
2   system comprising the steps of:

3                   receiving a multicarrier signal;

4                   applying Fast Fourier transformations to carriers of said multicarrier signal;

5                   estimating channel characteristics of a multicarrier channel over which said  
6   multicarrier signal was transmitted using iterative backward processing, wherein said  
7   iterative backward processing further comprises the steps of;

8                   determining if a block in a frame in the received signal is correct;

9                   tentatively decoding said block of said received signal;

10                  calculating a tentative reference signal based on a previous training block;

11                  generating a tentative estimation of channel characteristics using said tentative  
12   reference signal;

13                  decoding said block of said received signal;

14                  calculating a reference signal based on said received block;

15                  generating an estimation of channel characteristics using said reference signal;

16                  decrementing the block number;

17                  determining if the beginning of said frame has been reached;

18                  accepting a next block of received signal if said beginning of said frame has  
19   not been reached;

20 iteratively performing the steps above; and  
 21 decoding said transformed multicarrier signal.

1 17. The method according to claim 16, wherein said decoding steps are performed  
 2 using  $\hat{\mathbf{c}}_n = \arg \min_{\mathbf{c}_n} \sum_m \|\mathbf{x}_{m,n} - \hat{\mathbf{H}}_{m,n} \mathbf{c}_n\|^2$ .

1 18. The method according to claim 16, wherein said calculating steps are  
 2 performed using  $\tilde{\mathbf{H}}_{m,n} = \arg \min_{\mathbf{H}_{m,n}} \sum_m \|\mathbf{x}_{m,n} - \mathbf{H}_{m,n} \hat{\mathbf{c}}_n\|^2$ .

1 19. The method according to claim 16, wherein said first generating step is  
 2 performed using  $\sum_{l=1}^{M_L} \mathbf{B}_l \mathbf{d}(\tilde{\mathbf{H}}_{m,n+l-1}) - \mathbf{d}(\hat{\mathbf{H}}_{m,n}) = 0$

1 20. The method according to claim 16, wherein said second generating step is  
 2 performed using  $\sum_{l=1}^{M_L} \mathbf{B}_l \mathbf{d}(\tilde{\mathbf{H}}_{m,n+l-1}) - \mathbf{d}(\hat{\mathbf{H}}_{m,n-1}) = 0$ .

1 21. The method according to claim 16, wherein said decoding step further  
 2 comprises the steps of:  
 3 demodulating said multicarrier received signal;  
 4 combining said demodulated multicarrier signal using a maximum ratio  
 5 combiner; and  
 6 Viterbi decoding said combined signal.

1           22. The method according to claim 21, further comprising the step of  
2 deinterleaving said combined signal if said combined signal was interleaved for transmission.

1           23. The method according to claim 21, wherein said demodulating step is  
2 performed concurrently for all signals of said multicarrier signal.

1           24. The method according to claim 21, wherein said demodulating step is  
2 performed concurrently for all signals of said multicarrier signal.

1           25. The method according to claim 16, wherein said generating steps are  
2 performed using  $\sum_{l=1}^{M_L} \mathbf{B}_l^T \tilde{\mathbf{H}}_{m,n+l} - \hat{\mathbf{H}}_{m,n} = 0$ .

1           26. The method according to claim 16, wherein Fast Fourier transformations are  
2 applied to each carrier of said multicarrier signal.

1           27. A method for estimating channel characteristics in a multicarrier transmission  
2 system comprising the steps of:

3                   receiving a multicarrier signal;

4                   applying Fast Fourier transformations to carriers of said multicarrier signal;

5                   estimating channel characteristics of a multicarrier channel over which said  
6 multicarrier signal was transmitted concurrently using iterative processing and iterative  
7 backward processing; and

8                   decoding said transformed multicarrier signal.

1           28.    The method according to claim 27, wherein said iterative processing further  
2 comprises the steps of:

3                   determining if a block in a frame in the received signal is a training block;  
4                   tentatively decoding said block of said received signal;  
5                   calculating a tentative reference signal based on a previous training block;  
6                   generating a tentative estimation of channel characteristics using said tentative  
7 reference signal;  
8                   decoding said block of said received signal;  
9                   calculating a reference signal based on said received block;  
10                  generating an estimation of channel characteristics using said reference signal;  
11                  incrementing the block number;  
12                  determining if the end of said frame has been reached;  
13                  accepting a next block of received signal if said end of said frame has not  
14 been reached; and  
15                  iteratively performing the steps above.

1           29.    The method according to claim 27, wherein said interactive backward  
2 processing comprises the steps of:

3                   determining if a block in a frame in the received signal is correct;  
4                   tentatively decoding said block of said received signal;  
5                   calculating a tentative reference signal based on a previous training block;  
6                   generating a tentative estimation of channel characteristics using said tentative  
7 reference signal;

8 decoding said block of said received signal;  
 9 calculating a reference signal based on said received block;  
 10 generating an estimation of channel characteristics using said reference signal;  
 11 decrementing the block number;  
 12 determining if the beginning of said frame has been reached;  
 13 accepting a next block of received signal if said beginning of said frame has  
 14 not been reached; and  
 15 iteratively performing the steps above.

1 30. The method according to claim 27, wherein said decoding step further  
 2 comprises the steps of:

3 demodulating said multicarrier received signal;  
 4 combining said demodulated multicarrier signal using a maximum ratio  
 5 combiner; and  
 6 Viterbi decoding said combined signal;

1 31. The method according to claim 30, further comprising the step of  
 2 deinterleaving said combined signal if said combined signal was interleaved for transmission.

1 32. The method according to claim 30, wherein said demodulating step is  
 2 performed using QPSK techniques.

1 33. The method according to claim 7, wherein said demodulating step is  
 2 performed using QPSK techniques.



1           34.    The method according to claim 9, wherein said demodulating step is  
2 performed using QPSK techniques.

1           35.    The method according to claim 20, wherein said demodulating step is  
2 performed using QPSK techniques.

1           36.    The method according to claim 27, wherein Fast Fourier transformations are  
2 applied to each carrier of said multicarrier signal.